

Sigen Energy Gateway



- Multiple SigenStor connections supported for micro-grid system
- Seamless switchover, ensuring 0ms load-side disruption
- Built-in bypass circuit for enhanced system reliability
- Supports diesel generator connection & smart control
- Real-time current monitoring with 350ms anti-backflow protection

Sigen Energy Gateway for SigenStor

Sigen Gateway	C60-2	C120-6	C180-9	C300-12	C600	C1200	Units
Grid Connection							
Gridconnectiontype	Three phase						
Nominal AC voltage	380 ~ 400						V
Nominal AC current	91.2	182.4	274	456	912	1,824	A
Nominal AC power	60	120	180	300	600	1,200	kW
Nominal AC frequency	50 / 60						Hz
Disruptiontimeofbackupswitch ¹	0						ms
AC Output to Backup Port							
Nominal AC voltage	380 ~ 400						V
Nominal AC current	91.2	182.4	274	456	912	1,824	A
Nominal AC power	60	120	180	300	600	1,200	kW
Nominal AC frequency	50 / 60						Hz
Overvoltage category	III						
Inverter Connection							
Number of connection ports	2	6	9	12	30	50	
Nominal AC voltage	380 ~ 400						V
Max. AC input current	45.6						A
Smart Port Connection							
Generator output voltage	380 ~ 400						V
Nominal AC current	91.2	182.4	274	456	912	1,824	A
Nominal AC power	60	120	180	300	600	1,200	kW
Generator 2-wire start	Supported						
General Data							
Dimensions (W / H / D)	510 / 795 / 173	850 / 1,152 / 305	800 / 2,300 / 830		1,800 / 2,300 / 1,270		mm
Weight	35	74	350	400	1,100	1,300	kg
Storage temperature range	-40 ~ 70						°C
Operating temperature range 2	-30 ~ 55						°C
Relative humidity range	0% ~ 100%		0% ~ 95%		0% ~ 95%		
Max. operation altitude 2	4,000						m
Cooling	Natural convection		Natural convection		Smart air cooling		
Ingress protection rating	IP54		IP20		IP20		
Communication	Fast Ethernet, RS485, dry contact						
Installation method	Wall-mounted		Ground-mounted		Ground-mounted		

1. This refers to the load-side disruption time, to achieve this functionality Sigen Energy Gateway needs to be used together with Sigen Energy Controller and Sigen Battery. Test conditions: In the open-circuit state of the power grid, the nominal power of the Sigen Energy Controller is higher than the total power of the backup loads.
2. Please consult Sigenegy for detailed power derating information and customized requirements.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Sigenegy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in relation to any inaccuracies or omissions in this file.

